



Control intuitivo de la cámara para facilitar su uso y visibilidad

AW-RP150GJ

La AW-RP150 será el controlador de cámara remota más nuevo que complementará la completa línea de cámaras PTZ profesionales de Panasonic. Tiene la misma gran funcionalidad de los AW-RP120 y AW-RP50, y se une a la línea con mejoras significativas con respecto a esos modelos, incluido un nuevo joystick de operación con una sola mano (que controla PTZ o Focus) y una gran pantalla LCD táctil para monitoreo y configuración de menú

Key Features

Gran pantalla táctil para facilitar el uso

Nuevo joystick para manejo con una sola mano

Ajustes preestablecidos de cámara PTZ simplificados y memoria de seguimiento

Elementos de diseño intuitivos basados en la retroalimentación directa de los operadores de cámaras robóticas de todos los días

3G-SDI Active Through Output, 5 x RS-422, LAN PoE+, 2 x GPIO



AW-RP150GJ

<https://latam.connect.panasonic.com/bo/es/productos/broadcast-y-proav/aw-rp150gj>

General

| | |
|---------------------------------------|---|
| Power Requirements | 12 V DC (10.8 V to 13.2 V) |
| PoE+ | IEEE802.3at standard: DC 42 V to 57 V (Camera Input) |
| Current Consumption | 1.0 A (Connector Input) 0.6 A (PoE+ power supply) |
| Ambient Operating Temperature | 0 °C to 40 °C (32 °F to 104 °F) |
| Ambient Operating Humidity | 20% to 90% (no condensation) |
| Storage Temperature | -20 °C to 50 °C (-4 °F to 122 °F) |
| Peso | Approx. 3.2 kg (7.05 lb) |
| Dimensions (W x H x D) (mm) | 342 mm x 178 mm x 245 mm(excluding protrusions) |
| Dimensions (W x H x D) (inch) | 13-15/32 inches x 7 inches x 9-21/32 inches(excluding protrusions) |
| Controller Supported Equipment | IP/RS422 AW-UE150W/K, AW-HR140*1, AW-HE130W/K*1, AW-HN130W/K*1, AW-UE70W/K*1, AW-UN70W/K*1, AW-HE40 Series*1, AW-HN40HW/HK*1, AW-HE38HW/HK*1, AW-HN38HW/HK*1 |

Input/Output Connector

| | |
|---------------|---|
| Input | DC 12 V IN XLR 4-pin 3G-SDI IN SMPTE292 / 75 Ω (BNC x 1) Supported formats: 1080/59.94p*2, 1080/50p*2, 1080/59.94i, 1080/50i, 1080/23.98p, 1080/25p, 1080/23.98PsF, 1080/25PsF |
| Output | ACTIVE THRU OUT SMPTE292 / 75 Ω (BNC x 1) |

| | |
|--|---|
| Input/Output | <p>IP CONT:</p> <p>=====</p> <p>100BASE-TX</p> <p>-----</p> <p>PoE+ input</p> <p>-----</p> <p>Connection cable: LAN cable, max. 100 m (328 ft)</p> <ul style="list-style-type: none"> • When connecting the unit via a switching hub: <p>Straight cable or a cross cable (category 5 cable), STP (Shielded Twisted Pair) cable recommended</p> <ul style="list-style-type: none"> • When connecting the unit directly: Crossover cable (category 5 cable), STP (Shielded Twisted Pair) cable recommended <p>=====</p> <p>SERIAL CONT (RJ-45):</p> <p>=====</p> <p>RS-422 (control signals for remote cameras), TALLY OUT</p> <p>-----</p> <p>Connecting cable:</p> <p>Straight cable (category 5e or better shielded cable), max. 1000 m (3280 ft)</p> <p>-----</p> <p>TALLY OUT: Open collector output (negative logic)</p> <p>Maximum voltage resistance DC 24 V, Maximum current 50 mA</p> <p>=====</p> <p>TALLY/GPIO 1</p> <p>=====</p> <p>D-sub 25-pin, female, inch thread</p> <p>-----</p> <p>TALLY IN : 10 inputs (for receiving photocoupler signals)</p> <p>-----</p> <p>GPI : 6 inputs (for receiving photocoupler signals)</p> <p>GPIO : 5 inputs (for receiving photocoupler signals)</p> <p>or 5 outputs (open collector outputs, negative logic)</p> <ul style="list-style-type: none"> • Input/output switched with menu settings <p>=====</p> <p>GPIO 2</p> <p>=====</p> <p>D-sub 25-pin, female, inch thread</p> <p>-----</p> <p>GPI : 10 inputs (for receiving photocoupler signals)</p> <p>GPIO : 10 inputs (for receiving photocoupler signals) or 10 outputs (open collector outputs, negative logic)</p> <ul style="list-style-type: none"> • Input/output switched with menu settings <p>Reserve connectors:</p> <p>2 connectors (For future expansion feature)</p> |
| LCD Display | 7-inch Touch Panel GUI Monitor (WVGA (800×480)) |
| SD Memory Card Slot | SDHC / SDXC Memory Card Slot x 1 |
| Connection Specifications | |
| No. of Connectable Cameras | 200 (IP), 5 (RS422) |
| No. of Camera Selection Buttons | 10 |
| No. of Camera Groups | 20 (10 units per 1 group) |
| Memory | |
| Preset Memory | No. of memory : presets 100 |
| Tracing Memory | No. of cameras : Cam1 to Cam10 |
| | Recording time, no. of memory settings : Maximum 5 min. total per camera, maximum of 10 settings per camera |
| Other Functions | |
| No. of User Assignable Buttons | 6 + up to 10 on the LCD menu |
| Pan / Tilt Speed Adjustment | 7 levels |
| Tally LED display color | green / red |
| Note | *1: Connection with the AW-RP150GJ is planned for future support. Contact your sales representative for further information on when support will be available for this feature. Use may require a software version update. *2: Level-A support only. |

