



**Conveniently Compact Switcher Achieves High-quality Video**

## AV-HSW10

IP Live Switcher with intuitive and compact design takes online communication one level higher.

### Key Features

---

Diverse Interfaces to Suit Wide-ranging Needs

---

Diverse Keys for More Attractive Video

---

Multiviewer With 10 Selectable Patterns

---

Remote Control With Software Control Panel

AV-HSW10

<https://latam.connect.panasonic.com/br/es/productos/broadcast-y-proav/av-hsw10>

<b>Live Switcher -&gt; General-&gt; Power Supply</b>	16 V Dedicated Adaptor
<b>Live Switcher -&gt; General-&gt; Power Consumption</b>	3.0 A (48 W)
<b>Live Switcher -&gt; General-&gt; Operating Temperature</b>	0°C to 40 °C (32 °F to 104 °F)
<b>Live Switcher -&gt; General-&gt; Operating Humidity</b>	10 % to 90 % (no condensation)
<b>Live Switcher -&gt; General-&gt; Storage Temperature</b>	0 °C to 40 °C (32 °F to 104 °F)
<b>Live Switcher -&gt; General-&gt; Storage Humidity</b>	10 % to 90 % (no condensation)
<b>Live Switcher -&gt; General-&gt; Weight</b>	Approx. 1.8 kg ( Approx.3.96 lb)
<b>Live Switcher -&gt; General-&gt; Dimensions</b>	W 254 mm x H 67 mm x D 175 mm  (10 inches x 2-5/8 inches x 6-7/8 inches)  (excluding protrusions)
<b>Live Switcher -&gt; General-&gt; ME Number</b>	1 ME
<b>Live Switcher -&gt; Video Terminal-&gt; SDI IN</b>	4 lines
	<ul style="list-style-type: none"> <li>• Connectors: BNC x 4</li> <li>• Equipped with frame synchronizer</li> <li>• Connectors and have simplified format simple format converters, and have high-performance format converters.</li> <li>• Connectors to are equipped with simplified format converters.</li> <li>* SDI IN 1 excludes HDMI IN1.</li> </ul>
	[3G-SDI] 3G-SDI, SMPTE424 standard complied with (Compatible with Level-A/Level-B)
	<ul style="list-style-type: none"> <li>• 0.8 V [p-p] ± 10 % (75 Ω)</li> <li>• Automatic equalizer 100 m (when using a cable)</li> </ul>
	[HD-SDI] HD-SDI, SMPTE292M standard
	<ul style="list-style-type: none"> <li>• 0.8 V [p-p] ± 10 % (75 Ω)</li> <li>• Automatic equalizer 100 m (when using a cable)</li> </ul>

---

**Live Switcher -> Video Terminal -> HDMI IN** 2 lines, HDMI 1.4b compatible

Video format inputs:

720p/59.94 Hz, 720p/50 Hz, 1080i/59.94 Hz, 1080i/50 Hz, 1080p/59.94 Hz, 1080p/50 Hz, 1080p/29.97 Hz, 1080p/25 Hz, 1080p/24 Hz, 1080p/23.98

PC format inputs:

WSXGA+ (1680 x 1050, 60 Hz), SXGA (1280 x 1024, 60 Hz), WXGA (1280 x 768, 60 Hz), XGA (1024 x 768, 60 Hz)

Mode: Full/Fit-H/Fit-V

- Connectors: HDMI x 2
- Equipped with frame synchronizer and simplified color corrector.
- The HDMI IN connector has scaler function.
- This connector does not support the HDCP technologies.

\* HDMI IN 1 excludes SDI IN 1.

---

**Live Switcher -> Video Terminal -> SDI 2 lines OUT**

- Connectors: BNC x 2
- PGM, PVW, CLN, MV, AUX1/2, and Key Out can be assigned.

[3G-SDI] 3G-SDI, SMPTE424M standard complied with (Compatible with Level-A)

- 0.8 V [p-p]  $\pm$  10 % (75  $\Omega$ )

[HD-SDI] HD-SDI, SMPTE292M standard

- 0.8 V [p-p]  $\pm$  10 % (75  $\Omega$ )

---

**Live Switcher -> Video Terminal -> HDMI OUT** 1 line, HDMI 1.4b compatible

- Connector: HDMI x 1
- Equipped with scaler function.

Mode: Fit-V, Fit-H Full, Full-90%, Full-80%

- PGM, PVW, CLN, MV, AUX1/2, and Key Out can be assigned.
-

---

**Live Switcher -> Video Terminal ->  
LAN**

Compatible with 1000Base-T and AUTO-MDIX (for IP signal transmission/control)

- Connecting cable: LAN cable (Category 5e or more), max. 100 m (328 ft), STP (Shielded Twisted Pair) cable recommended

- Connector: RJ-45

IP input signal:

Assigned to IN 6 to 9.

- IN 6, IN 7: Selectable from SRT/NDI | HX (version1/version2).

- IN 8, IN 9: Dedicated to High Bandwidth NDI input.

Supports NDI a channel input. Used as a pair with IN 9 in this case.

- IN6 to 9: High Bandwidth NDI x4 can be selected by changing to firmware that supports NDI HB mode.

\*For H.264, the AV-HSW10 supports input up to Level 4.2.

For H.265, the AV-HSW10 supports input up to Level 5.1 (Main tier) and Level 4.1 (High tier).

IP output signal:

Assigned to OUT 4 and OUT 5.

- OUT 4, OUT 5: Selectable from SRT/High Bandwidth NDI/RTMP.

- PGM, PVW, CLN, MV, AUX1/2, Key Out can be assigned.

- Equipped with scaler function and i/p conversion function. \*1

- IN6 to IN9: When using firmware in NDI HB mode, only the High Bandwidth NDI of OUT4 is enabled.

- Possible output formats:

1920 x 1080/60fps, 50fps, 30fps, 25fps, 24fps, 1280 x 720/60fps, 50fps

\*For H.264, the AV-HSW10 outputs at Level 4.2.

For H.265, the AV-HSW10 outputs at Level 5 (Main tier).

---

---

**Live Switcher -> Video Terminal -> USB**Connector for outputting UVC/UAC

Assigned to OUT 6.

- Connector: USB3.2 Gen1 Type-C, No USB bus power functionality

- PGM, PVW, CLN, MV, AUX1/2, and Key Out can be assigned.

- Equipped with scaler function and i/p conversion function. \*1

- Possible output formats:

1920 x 1080/60fps, 50fps, 30fps, 25fps, 24fps, 1280 x 720/60fps, 50fps, 30fps, 25fps, 24fps

---

**Live Switcher -> Video Terminal -> Signal Formats**

3G-SDI

1080/59.94p, 50p, 29.97p, 25p, 24p, 23.98p

1080/59.94i, 50i,

720/59.94p, 50p

NDI® High Bandwidth

1080/59.94p, 50p, 29.97p, 25p, 24p, 23.98p

720/59.94p, 50p

NDI® HX

1080/60p, 50p, 30p, 25p, 24p

720p/60p, 50p

USB

1080/60p, 50p, 30p, 25p, 24p \*1

720p/60p, 50p, 30p, 25p, 24p

---

**Live Switcher -> Video Terminal -> Signal Processing**

[R:G:B] 4:4:4 8bit / 4:2:2 10bit (when HDMI)

[Y:Cb:Cr] 4:2:2 8bit (when NDI® High Bandwidth/UVC)

[Y:Cb:Cr] 4:2:0 8bit (when NDI® HX/SRT/RTMP)

[Y:Cb:Cr] 4:2:2 10bit

---

**Live Switcher -> Audio Terminal -> AUDIO IN**

L/1 and R/2

- Connector: Pin jacks

- Equipped with embedded functionality to each output.

- Equipped with delay/level adjustment function.

---

<b>Live Switcher -&gt; Audio Terminal -&gt; AUDIO OUT</b>	Connector for headphone monitor
	<ul style="list-style-type: none"> <li>• Connector: Ø3.5 mm TRS</li> <li>• Equipped with output volume adjustment function.</li> </ul>
<b>Live Switcher -&gt; Synchronous Terminal -&gt; REF Terminal Reference Input/ BB Outputs</b>	In Genlock mode: Selectable from BB (black burst), Tri-level Sync, and internal synchronization
	<ul style="list-style-type: none"> <li>• Loop-through output is performed in BB mode and Tri-level Sync mode.</li> <li>• If loop-through output is not going to be used, provide a 75 Ω termination.</li> <li>• Connectors: BNC×2</li> <li>• Same field frequencies as those of the system formats supported.</li> <li>• For 23.98 Hz and 24 Hz, only Tri-level input or internal synchronization is supported.</li> </ul>
<b>Live Switcher -&gt; Synchronous Terminal -&gt; Video Delay Time</b>	1 line (H)
	When the frame synchronizer setting is [Off] and neither the up-converter nor the down-converter is operating
	1 frame (F)
	When the frame synchronizer setting is on and the up-converter and downconverter are operating
	• When the signals have passed through PinP, multi view, down-converter or HDMI IN/OUT, a maximum delay of 1 frame is applied in each case.
<b>Live Switcher -&gt; Control Terminal -&gt; LAN Terminal</b>	Compatible with 1000Base-T and AUTO-MDIX (For IP control)
	<ul style="list-style-type: none"> <li>• Connecting cable: LAN cable (Category 5e), max. 100 m (328 ft), STP (Shielded Twisted Pair) cable recommended</li> <li>• Connector: RJ-45</li> </ul>
<b>Live Switcher -&gt; Control Terminal -&gt; TALLY GPI Terminal</b>	INPUT: 5 inputs, general-purpose, photocoupler sensing
	OUTPUT: 8 outputs, selected from R/G tally, general-purpose
	ALARM: 1 output, open collector output (negative logic)
	• Connectors: D-Sub 15pin
<b>Live Switcher -&gt; Control Terminal -&gt; USB Terminal</b>	• Connector: USB2.0, Type-A, with USB bus power functionality
	Use a USB memory to save and load configuration files and still data, and perform firmware updates.
<b>Live Switcher -&gt; Audio</b>	IN: RCA x 2, OUT: 3.5 mm TRS
<b>Live Switcher -&gt; Frame Synchronizer</b>	All inputs
<b>Live Switcher -&gt; CC/UC/DC (Input)</b>	i/P converter, DC/UC (1080-720P), CC
<b>Live Switcher -&gt; Keyer</b>	2 (PinP, Linear key, Luminance key, Chroma key*2)
<b>Live Switcher -&gt; AUX</b>	2
<b>Live Switcher -&gt; Genlock</b>	BB or Tri-level (Input/through output)
<b>Live Switcher -&gt; PTZ Link</b>	RP Link (AW-RP60/ RP150), TSL5.0
<b>Live Switcher -&gt; VMEM</b>	Still x 2
<b>Live Switcher -&gt; Shot MEM</b>	Max. 12 presets
<b>Footnote Description</b>	
	1. Planned support with a firmware update