



**Planned for launch in the first quarter of 2026**

## **AW-RP200GJ**

Next-generation Remote Camera Controller Revolutionizes Operator Workflows The AW-RP200GJ, building on its predecessor's (AW-RP150GJ) highly regarded operability, introduces powerful new features such as convenient macro functionality for executing complex camera operations with ease, and dual left and right joysticks for flexible control. Such innovations enhance the controller's performance for multi-camera productions, including in large-scale shooting environments, to elevate video content value.

### **Key Features**

20 multi-select switches for camera selection, preset recall and macro execution

Panasonic's first remote camera controller to support macro functionality

Handy second joystick on left (in addition to main joystick on right for pan, tilt, and zoom or focus control)

## AW-RP200GJ

<https://latam.connect.panasonic.com/pa/en/products/broadcast-proav/aw-rp200gj>

|                                                                        |                                                                                                      |
|------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------|
| <b>General -&gt; Power Requirements</b>                                | DC 12 V                                                                                              |
| <b>General -&gt; PoE</b>                                               | PoE++<br>IEEE802.3bt standard : DC 42 V to 57 V                                                      |
| <b>General -&gt; Weight</b>                                            | Approx. 3.5 kg ( 7.72 lb )                                                                           |
| <b>General -&gt; Dimensions</b>                                        | 364 mm x 178 mm x 245 mm<br>(14-11/32 inches x 7 inches x 9-21/32 inches)<br>(excluding protrusions) |
| <b>Input Connector -&gt; DC IN</b>                                     | DC 12 V IN, XLR 4-pin                                                                                |
| <b>Input/Output Connector -&gt; LAN ( IP CONT )</b>                    | LAN (RJ-45)                                                                                          |
| <b>Input/Output Connector -&gt; TALLY / GPIO 1</b>                     | GPIO x2 (DSUB 25-pin)                                                                                |
| <b>Input/Output -&gt; LCD Display</b>                                  | 7-inch Touch Panel GUI Monitor (WVGA(800×480))                                                       |
| <b>Connection Specifications -&gt; No. of Connectable Cameras</b>      | 200 (IP), 3 (RS-422)                                                                                 |
| <b>Connection Specifications -&gt; No. of Camera Selection Buttons</b> | 20                                                                                                   |
| <b>Memory -&gt; Preset Memory</b>                                      | No. of memory presets 100 per camera                                                                 |
| <b>Memory -&gt; Tracing Memory</b>                                     | Maximum of 10 settings per camera (CAM1 ~ 10)                                                        |
| <b>Input Connector -&gt; 3G SDI IN</b>                                 | SMPTE424M/SMPTE292M/75Ω ( BNC×1 )                                                                    |
| <b>Output Connector -&gt; 3G SDI OUT</b>                               | SMPTE424M/SMPTE292M/75Ω ( BNC×1 )                                                                    |
| <b>Input/Output Connector -&gt; LAN (SERIAL CONT 1-3)</b>              | RS-422 x3 (RJ-45)                                                                                    |
| <b>Input/Output Connector -&gt; USB Port</b>                           | USB Type-A/Type-C (USB2.0)                                                                           |
| <b>Memory -&gt; Macro Memory</b>                                       | No. of macros 100                                                                                    |