# Panasonic CONNECT



#### Planned for launch in the fourth quarter of 2025

## AK-UBX100

Panasonic is Creating the Future of Video Production with More Flexibility. More Precision. And More True to You. The AK-UBX100 box-style 4K multi-purpose camera utilizes the same main functional and original core design and shared menu interface as the AK-UCX100 4K studio camera. This eliminates the complexity of color matching, which has been a longstanding issue, and unifies operability across devices. Also, by utilizing a common remote operation panel (ROP), seamless integration with the AK-UCX100 4K studio camera and the AW-UE160 4K PTZ camera becomes possible, leading to significant improvements in operational efficiency on the shooting site. The AK-UBX100 independently supports a variety of IP protocols including SMPTE ST 2110, NDI®, SRT and its interfaces include two 12G-SDI ports and two SFP28 ports. In addition to basic moiré reduction performance designed for various production needs, the addition of

#### **Key Features**

The same platform as the AK-UCX100

Lightweight and compact design

Autofocus support planned

2,000 TVL resolution

Supports a wide range of interfaces including 12G-SDI (×2 channels), SMPTE ST 2110, NDI High Bandwidth, and SRT





### AK-UBX100

https://latam.connect.panasonic.com/ar/en/products/broadcast-proav/ak-ubx100

General -> Power Supply	DC 12 V ( DC11V - 17V )
General -> Power Consumption	40 W (body only, when outputting 12G SDI)
	60 W (maximum power when all accessories are connected and each output terminal is
Canadal > One wating Tamanagating	outputting at maximum)
General -> Operating Temperature	-10 °C to 45 °C (14 °F to 113 °F) (Preheating required under a temperature 0°C (32 °F) or below)
ieneral -> Operating Humidity	85% or less (relative humidity)
Seneral -> Storage Temperature	-20 °C to 60 °C (-4 °F to 140 °F)
ieneral -> Weight	Approx. 1.9 kg (4.19 lbs.) (body only)
General -> Dimensions	118 mm x 140 mm x 175 mm(4-21/32 inches x 5-17/32 inches x 6-57/64 inches)
	(excluding protrusions)
Camera Unit -> Pickup Device	19.29 million pixels, MOS sensor
Camera Unit -> Optical Filter -> ND	CLEAR, 1/2, 1/4, 1/16, 1/64
Camera Unit -> Optical Filter -> FX	*Option: HD-Optical Low Pass filter
Camera Unit -> Lens Mount	2/3-type bayonet
Camera Unit -> Sensitivity	[LOW LIGHT]: F10(59.94 Hz)/F11(50 Hz)
	[NORMAL]: F6(59.94 Hz)/F7(50 Hz)
	2000 Ix, 3200 K, when white reflectivity is 89.9%
amera Unit -> Horizontal Resolution HD	-1000 IV lines or above (center)
Camera Unit -> S/N	62 dB or above
amera Unit -> Gain Switching -> IORMAL	-6, -3, 0, 3, 6, 9, 12, 15, 18
Camera Unit -> Shutter Speed -> 59.94i]/[59.94p] mode	1/100, 1/120, 1/125, 1/250, 1/500, 1/1000, 1/1500, 1/2000
Camera Unit -> Shutter Speed -> 50i]/[50p] mode	1/60, 1/100, 1/125, 1/250, 1/500, 1/1000, 1/1500, 1/2000
Camera Unit -> Shutter Speed ->	1/48, 1/50, 1/60, 1/96, 1/100, 1/120, 1/125, 1/250, 1/500, 1/1000, 1/1500, 1/2000
29.97p] mode	
Camera Unit -> Shutter Speed -> [25p node	]1/48, 1/50, 1/60, 1/96, 1/100, 1/125, 1/250, 1/500, 1/1000, 1/1500, 1/2000
amera Unit -> Shutter Speed -> 23.98p] mode	1/48, 1/50, 1/60, 1/96, 1/100, 1/120, 1/125, 1/250, 1/500, 1/1000, 1/1500, 1/2000
Camera Unit	3840x2160/59.94p/50p/29.97p/25p/23.98p 1920x1080/59.94p/50p/29.97p/25p/23.98p
Other Input/Output -> < SFP 2 > Ferminal	SFP+/28 x 1
Other Input/Output -> < SFP 1 > Ferminal	SFP+/28 x 1
Other Input/Output - > < LENS > Ferminal	12-pin x 1
Other Input/Output - > < DC IN > Ferminal	XLR x 1, 4-pin, DC12 V ( DC11V - 17V )
Other Input/Output - > < REMOTE > Ferminal	10-pin x 1
Other Input/Output - > < LAN > Ferminal	RJ-45 x 1
/ideo Input/Output - > < 12G SDI OUT	
> Terminal	12G/6G/3G/1.5G-SDI: 0.8 V [ p-p ] 、75 Ω
/ideo Input/Output - > < 12G SDI OUT	
! > Terminal	12G/6G/3G/1.5G-SDI: 0.8 V [ p-p ] 、75 Ω
/ideo Input/Output - > < HD SDI OUT > 'erminal	
erminai /ideo Input/Output - > < G/L IN >	3G/1.5G-SDI: 0.8 V [p-p]、75 Ω BNC × 1
erminal	1 V [p-p] 、75 Ω
Other Input/Output - > < TALLY OUT >	-, , -
erminal	•
amera Unit -> Horizontal Resolution	-2000 TV lines or above (center)
Camera Unit -> Synchro Scan Shutter · [59.94i]/[59.94p] mode	-60.0 Hz to 7200 Hz
Camera Unit -> Synchro Scan Shutter > [50i]/[50p] mode	-50.0 Hz to 7200 Hz
Camera Unit -> Synchro Scan Shutter > [29.97p] mode	-30.0 Hz to 7200 Hz
Camera Unit -> Synchro Scan Shutter > [25p] mode	-25.0 Hz to 7200 Hz
Camera Unit -> Synchro Scan Shutter	-24.0 Hz to 7200 Hz

> [23.98p] mode