



El control intuitivo de la cámara, que facilita el uso y la visibilidad

AW-RP150GJ

El AW-RP150 es el último modelo de controlador de cámaras remotas que se incorpora a la completa gama de cámaras PTZ profesionales de Panasonic.

Key Features

Pantalla táctil de gran tamaño para mayor facilidad de uso

Nuevo joystick que se maneja con una sola mano

Ajustes preestablecidos simplificados para la cámara PTZ y memoria de seguimiento

Elementos de diseño intuitivos basados en los comentarios directos de los operadores de cámaras robóticas que las utilizan a diario

Salidas activas 3G-SDI, 5 x RS-422, LAN PoE+, 2 x GPIO



AW-RP150GJ

<https://latam.connect.panasonic.com/co/es/productos/broadcast-y-proav/aw-rp150gj>

General

Power Requirements	12 V DC (10.8 V to 13.2 V)
PoE+	IEEE802.3at standard: DC 42 V to 57 V (Camera Input)
Current Consumption	1.0 A (Connector Input) 0.6 A (PoE+ power supply)
Ambient Operating Temperature	0 °C to 40 °C (32 °F to 104 °F)
Ambient Operating Humidity	20% to 90% (no condensation)
Storage Temperature	-20 °C to 50 °C (-4 °F to 122 °F)
Peso	Approx. 3.2 kg (7.05 lb)
Dimensions (W x H x D) (mm)	342 mm x 178 mm x 245 mm(excluding protrusions)
Dimensions (W x H x D) (inch)	13-15/32 inches x 7 inches x 9-21/32 inches(excluding protrusions)
Controller Supported Equipment	IP/RS422

AW-UE150W/K, AW-HR140*1, AW-HE130W/K*1, AW-HN130W/K*1, AW-UE70W/K*1, AW-UN70W/K*1, AW-HE40 Series*1, AW-HN40HW/HK*1, AW-HE38HW/HK*1, AW-HN38HW/HK*1

Input/Output Connector

Input	DC 12 V IN XLR 4-pin 3G-SDI IN SMPTE292 / 75 Ω (BNC x 1) Supported formats: 1080/59.94p*2, 1080/50p*2, 1080/59.94i, 1080/50i, 1080/23.98p, 1080/25p, 1080/23.98PsF, 1080/25PsF
Output	ACTIVE THRU OUT SMPTE292 / 75 Ω (BNC x 1)
Input/Output	IP CONT:

=====

100BASE-TX

PoE+ input

Connection cable: LAN cable, max. 100 m (328 ft)

· When connecting the unit via a switching hub:

Straight cable or a cross cable (category 5 cable), STP (Shielded Twisted Pair) cable recommended

· When connecting the unit directly: Crossover cable (category 5 cable), STP (Shielded Twisted Pair) cable recommended

=====

SERIAL CONT (RJ-45):

=====

RS-422 (control signals for remote cameras), TALLY OUT

Connecting cable:

Straight cable (category 5e or better shielded cable), max. 1000 m (3280 ft)

TALLY OUT: Open collector output (negative logic)

Maximum voltage resistance DC 24 V, Maximum current 50 mA

=====

TALLY/GPIO 1

=====

D-sub 25-pin, female, inch thread

TALLY IN : 10 inputs (for receiving photocoupler signals)

GPI : 6 inputs (for receiving photocoupler signals)

GPIO : 5 inputs (for receiving photocoupler signals)

or 5 outputs (open collector outputs, negative logic)

- Input/output switched with menu settings

=====

GPIO 2

=====

D-sub 25-pin, female, inch thread

GPI : 10 inputs (for receiving photocoupler signals)

GPIO : 10 inputs (for receiving photocoupler signals) or 10 outputs (open collector outputs, negative logic)

- Input/output switched with menu settings

Reserve connectors:

2 connectors (For future expansion feature)

LCD Display 7-inch Touch Panel GUI Monitor (WGA (800×480))

SD Memory Card Slot SDHC / SDXC Memory Card Slot x 1

Connection Specifications

No. of Connectable Cameras 200 (IP), 5 (RS422)

No. of Camera Selection Buttons 10

No. of Camera Groups 20 (10 units per 1 group)

Memory

Preset Memory No. of memory : presets 100

Tracing Memory No. of cameras : Cam1 to Cam10

Recording time, no. of memory settings : Maximum 5 min. total per camera, maximum of 10 settings per camera

Other Functions

No. of User Assignable Buttons 6 + up to 10 on the LCD menu

Pan / Tilt Speed Adjustment 7 levels

Tally LED display color green / red

Note

*1: Connection with the AW-RP150Gj is planned for future support. Contact your sales representative for further information on when support will be available for this feature. Use may require a software version update. *2: Level-A support only.