



Lanzamiento previsto para el primer trimestre de 2026

AW-RP200GJ

El controlador remoto de cámara de próxima generación revoluciona los flujos de trabajo de los operadores. El AW-RP200GJ, basado en la operatividad altamente reconocida de su predecesor (AW-RP150GJ), presenta nuevas y poderosas características, como una conveniente funcionalidad macro para ejecutar operaciones complejas de la cámara con facilidad y joysticks duales izquierdo y derecho para un control flexible. Estas innovaciones mejoran el rendimiento del controlador para producciones multicámara, incluso en entornos de grabación a gran escala, para elevar el valor del contenido de video.

Key Features

20 interruptores de selección múltiple para selección de cámara, recuperación de preajustes y ejecución macro

El primer controlador remoto de cámara de Panasonic compatible con la funcionalidad macro

Práctico segundo joystick a la izquierda (además del joystick principal a la derecha para el control de giro, inclinación y zoom o enfoque)

AW-RP200GJ

<https://latam.connect.panasonic.com/mx/es/productos/broadcast-y-proav/aw-rp200gj>

| | |
|--|--|
| General -> Power Requirements | DC 12 V |
| General -> PoE | PoE++ IEEE802.3bt standard : DC 42 V to 57 V |
| General -> Weight | Approx. 3.5 kg (7.72 lb) |
| General -> Dimensions | 364 mm x 178 mm x 245 mm (14-11/32 inches x 7 inches x 9-21/32 inches) (excluding protrusions) |
| Input Connector -> DC IN | DC 12 V IN, XLR 4-pin |
| Input/Output Connector -> LAN (IP CONT) | LAN (RJ-45) |
| Input/Output Connector -> TALLY / GPIO 1 | GPIO x2 (DSUB 25-pin) |
| Input/Output -> LCD Display | 7-inch Touch Panel GUI Monitor (WVGA(800×480)) |
| Connection Specifications -> No. of Connectable Cameras | 200 (IP), 3 (RS-422) |
| Connection Specifications -> No. of Camera Selection Buttons | 20 |
| Memory -> Preset Memory | No. of memory presets 100 per camera |
| Memory -> Tracing Memory | Maximum of 10 settings per camera (CAM1 ~ 10) |
| Input Connector -> 3G SDI IN | SMPTE424M/SMPTE292M/75Ω (BNC×1) |
| Output Connector -> 3G SDI OUT | SMPTE424M/SMPTE292M/75Ω (BNC×1) |
| Input/Output Connector -> LAN (SERIAL CONT 1-3) | RS-422 x3 (RJ-45) |
| Input/Output Connector -> USB Port | USB Type-A/Type-C (USB2.0) |
| Memory -> Macro Memory | No. of macros 100 |