



Lançamento previsto para o primeiro trimestre de 2026

AW-RP200GJ

O controlador de câmera remota de última geração revoluciona os fluxos de trabalho do operador. O AW-RP200GJ, com base na operabilidade altamente conceituada de seu antecessor (AW-RP150GJ), apresenta novos recursos poderosos, como a conveniente funcionalidade macro para executar operações complexas da câmera com facilidade e joysticks duplos esquerdo e direito para controle flexível. Essas inovações aprimoram o desempenho do controlador para produções com várias câmeras, inclusive em ambientes de filmagem em grande escala, para elevar o valor do conteúdo de vídeo.

Key Features

20 interruptores de seleção múltipla para seleção de câmera, recuperação predefinida e execução de macro

O primeiro controlador de câmera remota da Panasonic a suportar a funcionalidade macro

Segundo joystick prático à esquerda (além do joystick principal à direita para controle de panorâmica, inclinação e zoom ou foco)

AW-RP200GJ

<https://latam.connect.panasonic.com/mx/pt/produtos/broadcast-proav/aw-rp200gj>

General -> Power Requirements	DC 12 V
General -> PoE	PoE++ IEEE802.3bt standard : DC 42 V to 57 V
General -> Weight	Approx. 3.5 kg (7.72 lb)
General -> Dimensions	364 mm x 178 mm x 245 mm (14-11/32 inches x 7 inches x 9-21/32 inches) (excluding protrusions)
Input Connector -> DC IN	DC 12 V IN, XLR 4-pin
Input/Output Connector -> LAN (IP CONT)	LAN (RJ-45)
Input/Output Connector -> TALLY / GPIO 1	GPIO x2 (DSUB 25-pin)
Input/Output -> LCD Display	7-inch Touch Panel GUI Monitor (WVGA(800×480))
Connection Specifications -> No. of Connectable Cameras	200 (IP), 3 (RS-422)
Connection Specifications -> No. of Camera Selection Buttons	20
Memory -> Preset Memory	No. of memory presets 100 per camera
Memory -> Tracing Memory	Maximum of 10 settings per camera (CAM1 ~ 10)
Input Connector -> 3G SDI IN	SMPTE424M/SMPTE292M/75Ω (BNC×1)
Output Connector -> 3G SDI OUT	SMPTE424M/SMPTE292M/75Ω (BNC×1)
Input/Output Connector -> LAN (SERIAL CONT 1-3)	RS-422 x3 (RJ-45)
Input/Output Connector -> USB Port	USB Type-A/Type-C (USB2.0)
Memory -> Macro Memory	No. of macros 100