



4K/12G-SDI compatible, compact Live Switcher.

AV-UHS500

The 4K Live Switcher is easy to use in a variety of applications, such as event staging, broadcast at stations and OB vans, lectures at universities, conference halls and so on, demonstrating incredible performance in live video production on the field.

Key Features

Versatile 12G-SDI/3G-SDI/HDMI interface support

UHD/HD multi-format support Expanded functions with two optional unit slots

Standard number of inputs/outputs: 8 inputs / 7 outputs

Maximum number of inputs/outputs (with optional boards): Maximum 16 inputs/Maximum 15 outputs

Five keyers for excellent image effects

HDMI™
HIGH DEFINITION MULTIMEDIA INTERFACE





AV-UHS500

<https://latam.connect.panasonic.com/pa/en/av-uhs500>

Live Switcher -> General -> Power Supply	AC 100 V to 240 V, 50 Hz/60 Hz
Live Switcher -> General -> Power Consumption	1.5 A
Live Switcher -> General -> Operating Temperature	0°C to 40 °C (32 °F to 104 °F)
Live Switcher -> General -> Operating Humidity	10 % to 90 % (no condensation)
Live Switcher -> General -> Storage Temperature	0 °C to 40 °C (32 °F to 104 °F)
Live Switcher -> General -> Storage Humidity	10 % to 90 % (no condensation)
Live Switcher -> General -> Weight	Approx. 7 kg (Approx.15.4 lb)
Live Switcher -> General -> Dimensions	W 440 mm x H 170 mm x D 360 mm (17-5/16 inches x 6-11/16 inches x 14-3/16 inches) (excluding protrusions)
Live Switcher -> General -> ME Number	1 ME
Live Switcher -> Video Terminal -> SDI IN	8 lines (plus another maximum of 8 lines when using the OPTION unit) <ul style="list-style-type: none"> • Connectors: BNC x 8 • Color space conversion function • Frame synchronizer function • Connectors to equipped with simple format converters. • Connectors to equipped with up-converters. • Connectors to equipped with color correctors. <p>* SDI IN 1/2 excludes HDMI IN 1/2.</p> <p>[1G-SDI] SMPTE ST 2082-10 standard complied with</p> <p>[3G-SDI] 3G-SDI, SMPTE292 standard complied with (Compatible with Level-A/Level-B)</p> <p>[HD-SDI] HD-SDI, SMPTE292M standard complied with</p>
Live Switcher -> Video Terminal -> HDMI IN	2 lines (plus another maximum of 6 lines when using the OPTION unit) <p>Video format inputs:</p> <p>720p/59.94 Hz, 720p/50 Hz, 1080i/59.94 Hz, 1080i/50 Hz, 1080p/59.94 Hz, 1080p/50 Hz, 1080p/29.97 Hz, 1080p/25 Hz, 1080p/24 Hz, 1080p/23.98 Hz, 2160p/59.94 Hz, 2160p/50 Hz, 2160p/29.97 Hz, 2160p/25 Hz, 2160p/24 Hz, 2160p/23.98 Hz</p> <p>PC format inputs:</p> <p>4K (3840 x 2160, 60 Hz), WQHD (2560 x 1440, 60 Hz), WUXGA (1920 x 1200, 60 Hz), UXGA (1600 x 1200, 60 Hz), WSXGA+ (1680 x 1050, 60 Hz), SXGA (1280 x 1024, 60 Hz), WXGA (1280 x 768, 60 Hz), XGA (1024 x 768, 60 Hz)</p> <p>Mode: Full/Fit-H/Fit-V</p> <ul style="list-style-type: none"> • Scaler, Frame synchronizer and Color space conversion function • Connectors: HDMI x 2 • This connector does not support the CPRM technologies. <p>* HDMI IN 1/2 excludes SDI IN 1/2.</p>

Live Switcher -> Video Terminal -> SDI OUT	<ul style="list-style-type: none"> • Connectors: BNC x 5 • Down-converter to 1080p, Color space conversion function • PGM, PVW, CLN, ME PGM, MV1 to MV2, AUX1 to AUX4, Key Out can be assigned. <p>[12G-SDI] SMPTE ST 2082-10 standard complied with</p> <p>[3G-SDI] SMPTE292 standard complied with (Compatible with Level-A)</p> <p>[HD-SDI] SMPTE292M standard complied with</p>
Live Switcher -> Video Terminal -> HDMI OUT	<p>2 lines (plus another maximum of 6 lines when using the OPTION unit)</p> <ul style="list-style-type: none"> • Connectors: HDMI x 2 • Not support Scaler (Only system format is available) • Color space conversion function • PGM, PVW, CLN, ME PGM, MV1 to MV2, AUX1 to AUX4, Key Out can be assigned.
Live Switcher -> Video Terminal -> Signal Formats	<p>2160/59.94p, 50p, 29.97p, 25p, 24p, 23.98p,</p> <p>1080/59.94p, 50p, 29.97p, 29.97PsF, 25p, 25PsF, 24p, 24PsF, 23.98p, 23.98PsF, 59.94i, 50i</p> <p>720/59.94p, 50p</p>
Live Switcher -> Video Terminal -> Signal Processing	<p>[R: G: B] 4: 4: 8 bit / 4: 2: 2 10 bit (Only for HDMI)</p> <p>[Y: Cb: Cr] 4: 2: 2 10 bit</p>
Live Switcher -> Synchronous Terminal -> REF Terminal Reference Input/ BB Outputs	<p>In Genlock mode: Black burst or Tri-level Sync input signals (with loop-through)</p> <ul style="list-style-type: none"> • Loop-through output is performed in external sync mode. • If loop-through output is not going to be used, provide a 75 Ω termination. • Connectors : BNC x 2 • Same field frequencies as those of the system formats supported. • With the 24.00p format, Black Burst input signal is not supported. • With the 1080/23.98PsF format, black burst with 10 Field ID (SMPTE318M standard met) or Trilevel Sync signals supported. • BB signals are output from two connectors in the internal sync mode.
Live Switcher -> Synchronous Terminal -> Video Delay Time	<p>1 line (H)</p> <p>When the frame synchronizer setting is [Off] and neither the up-converter nor the down-converter is operating</p> <p>1 frame (F)</p> <p>When the frame synchronizer setting is [On] and the up-converter and down-converter are operating</p> <ul style="list-style-type: none"> • When the signals have passed through PinP, DVE, multi view, down-converter or HDMI IN, a maximum delay of 1 frame is applied in each case.
Live Switcher -> Control Terminal -> LAN Terminal	<p>Compatible with 1000BASE-TX and AUTO-MDIX (For IP control)</p> <ul style="list-style-type: none"> • Connecting cable: LAN cable (CAT5e), max. 100 m (328 ft), STP (Shielded Twisted Pair) cable recommended • Connectors : RJ-45
Live Switcher -> Control Terminal -> TALLY GPI Terminal	<p>INPUT: 8 inputs general-purpose, photocoupler sensing</p> <p>OUTPUT: 19 outputs; selected from R/G tally, general-purpose</p> <p>ALARM: 1 output, open collector output (negative logic)</p>
Option Unit AV-UHSSM1G / AV-UHSSM2G / AV-UHSSM3G / AV-UHSSM4G / AV-UHSSM5G / AV-UHSSM6G -> General -> Power Supply	<p>DC 12 V Supplied by AV-UHSS00</p>
Option Unit AV-UHSSM1G / AV-UHSSM2G / AV-UHSSM3G / AV-UHSSM4G / AV-UHSSM5G / AV-UHSSM6G -> General -> Power Consumption	<p>AV-UHSSM1G/AV-UHSSM2G: 15 W 1.2 A</p> <p>AV-UHSSM3G/AV-UHSSM4G: 16 W 1.3 A</p> <p>AV-UHSSM5G/AV-UHSSM6G: 14 W 1.1 A</p>
Option Unit AV-UHSSM1G / AV-UHSSM2G / AV-UHSSM3G / AV-UHSSM4G / AV-UHSSM5G / AV-UHSSM6G -> General -> Operating Temperature	<p>10 % to 90 % (no condensation)</p>
Option Unit AV-UHSSM1G / AV-UHSSM2G / AV-UHSSM3G / AV-UHSSM4G / AV-UHSSM5G / AV-UHSSM6G -> General -> Operating Humidity	<p>0 °C to 40 °C (32 °F to 104 °F)</p>
Option Unit AV-UHSSM1G / AV-UHSSM2G / AV-UHSSM3G / AV-UHSSM4G / AV-UHSSM5G / AV-UHSSM6G -> General -> Storage Temperature	<p>10 % to 90 % (no condensation)</p>

Option Unit AV-UHS5M1G / AV-UHS5M2G / AV-UHS5M3G / AV-UHS5M4G / AV-UHS5M5G / AV-UHS5M6G -> General -> Storage Humidity	0 °C to 40 °C (32 °F to 104 °F)
Option Unit AV-UHS5M1G / AV-UHS5M2G / AV-UHS5M3G / AV-UHS5M4G / AV-UHS5M5G / AV-UHS5M6G -> General -> Weight	<p>AV-UHS5M1G/AV-UHS5M2G: Approx. 371 g (Approx. 0.82 lbs.)</p> <p>AV-UHS5M3G/AV-UHS5M4G: Approx. 353 g (Approx. 0.78 lbs.)</p> <p>AV-UHS5M5G: Approx. 345 g (Approx. 0.76 lbs.)</p> <p>AV-UHS5M6G: Approx. 353 g (Approx. 0.78 lbs.)</p>
Option Unit AV-UHS5M1G / AV-UHS5M2G / AV-UHS5M3G / AV-UHS5M4G / AV-UHS5M5G / AV-UHS5M6G -> General -> Dimensions	<p>AV-UHS5M1G/AV-UHS5M2G: W 112 mm x H 42 mm x D 167 mm (4-13/32 inches x 1-21/32 inches x 6-9/16 inches) (excluding protrusions)</p> <p>AV-UHS5M3G/AV-UHS5M4G/AV-UHS5M5G/AV-UHS5M6G: W 112 mm x H 42 mm x D 166 mm (4-13/32 inches x 1-21/32 inches x 6-17/32 inches) (excluding protrusions)</p>
Option Unit AV-UHS5M1G / AV-UHS5M2G / AV-UHS5M3G / AV-UHS5M4G / AV-UHS5M5G / AV-UHS5M6G -> SDI Input Unit AV-UHS5M1G -> SDI IN 1 to SDI IN 4 Terminals	<p>4 lines</p> <ul style="list-style-type: none"> • Connectors: BNC x 4 • Frame synchronizer function • Up-converter fitted. • Color space conversion function • Color corrector fitted. <p>[12G-SDI]</p> <p>12G Serial digital, SMPTE ST 2082-10 standard complied with</p> <ul style="list-style-type: none"> • 0.8 V [p-p] ± 10 % (75 Ω) • Automatic equalizer 80 m (when the cable is used) <p>[3G-SDI]</p> <p>3G Serial digital, SMPTE292 standard complied with (Level-A/Level-B)</p> <ul style="list-style-type: none"> • 0.8 V [p-p] ± 10 % (75 Ω) • Automatic equalizer 100 m (when the cable is used) <p>[HD-SDI]</p> <p>HD Serial digital, SMPTE292M standard complied with</p> <ul style="list-style-type: none"> • 0.8 V [p-p] ± 10 % (75 Ω) • Automatic equalizer 100 m (when the cable is used)
Option Unit AV-UHS5M1G / AV-UHS5M2G / AV-UHS5M3G / AV-UHS5M4G / AV-UHS5M5G / AV-UHS5M6G -> SDI Input Unit AV-UHS5M2G -> SDI OUT 1 to SDI OUT 4 Terminals	<p>4 lines</p> <ul style="list-style-type: none"> • Connectors: BNC x 4 • Down-converter • Color space conversion function • PGM, PVW, CLN, ME PGM, MV1 to MV2, AUX1 to AUX4, Key Out can be assigned. <p>[12G-SDI]</p> <p>12G Serial digital, SMPTE ST 2082-10 standard complied with 0.8 V [p-p] ± 10 % (75 Ω)</p> <p>[3G-SDI]</p> <p>3G Serial digital, SMPTE292 standard complied with (Level-A) 0.8 V [p-p] ± 10 % (75 Ω)</p> <p>[HD-SDI]</p> <p>HD Serial digital, SMPTE292M standard complied with 0.8 V [p-p] ± 10 % (75 Ω)</p>

Option Unit AV-UHSSM1G / AV-UHSSM2G / AV-UHSSM3G / AV-UHSSM4G / AV-UHSSM5G / AV-UHSSM6G -> SDI Input Unit AV-UHSSM3G -> HDMI IN 1 to HDMI IN 3 Terminals	<p>3 lines</p> <p>Video format inputs:</p> <p>720p/59.94 Hz, 720p/50 Hz, 1080i/59.94 Hz, 1080i/50 Hz, 1080p/59.94 Hz, 1080p/50 Hz, 1080p/29.97 Hz, 1080p/25 Hz,</p> <p>1080p/24 Hz, 1080p/23.98 Hz, 2160p/59.94 Hz, 2160p/50 Hz, 2160p/29.97 Hz, 2160p/25 Hz, 2160p/24 Hz, 2160p/23.98 Hz</p> <p>PC format inputs:</p> <p>4K (3840 x 2160, 60 Hz), WQHD (2560 x 1440, 60 Hz), WUXGA (1920 x 1200, 60 Hz), UXGA (1600 x 1200, 60 Hz),</p> <p>WSXGA+ (1680 x 1050, 60 Hz), SXGA (1280 x 1024, 60 Hz), WXGA (1280 x 768, 60 Hz), XGA (1024 x 768, 60 Hz)</p> <p>Mode: Full/Fit-H/Fit-V</p> <ul style="list-style-type: none"> • Connectors: HDMI x 3 • Frame synchronizer function • Color corrector fitted. • Scaler and Color space conversion function • This connector does not support the CPRM technologies.
Option Unit AV-UHSSM1G / AV-UHSSM2G / AV-UHSSM3G / AV-UHSSM4G / AV-UHSSM5G / AV-UHSSM6G -> SDI Input Unit AV-UHSSM4G -> HDMI OUT 1 to HDMI OUT 3 Terminals	<p>3 lines</p> <p>Mode: Fit-V, Fit-H, Full, Full-90 %, Full-80 %</p> <p>Size: Auto, WQHD (2560 x 1440, 60 Hz), WUXGA (1920 x 1200, 60 Hz), UXGA (1600 x 1200, 60 Hz), WSXGA+ (1680 x 1050, 60 Hz),</p> <p>SXGA (1280 x 1024, 60 Hz), WXGA (1280 x 768, 60 Hz), XGA (1024 x 768, 60 Hz), Native</p> <p>Color: Auto, RGB, YUV444, YUV422</p> <ul style="list-style-type: none"> • Connectors: HDMI x 3 • PGM, PVW, CLN, ME PGM, MV1 to MV2, AUX1 to AUX4, Key Out can be assigned. • Scaler and Color space conversion function
Option Unit AV-UHSSM1G / AV-UHSSM2G / AV-UHSSM3G / AV-UHSSM4G / AV-UHSSM5G / AV-UHSSM6G -> SDI Input Unit AV-UHSSM5G -> LAN 1 and LAN 2 Terminals	<p>Supported formats</p> <p>NDI® High Bandwidth/NDI® HX *1</p> <p>Input</p> <p>Maximum 4 lines</p> <p>Possible input formats</p> <ul style="list-style-type: none"> • When system format is 4K <p>NDI® High Bandwidth: 2160/59.94p, 2160/50p, 2160/29.97p, 2160/25p, 2160/24p, 2160/23.98p</p> <ul style="list-style-type: none"> • When system format is 2K *1 *2 *3 *4 <p>NDI® High Bandwidth: 1080/59.94p, 1080/50p, 1080/29.97p, 1080/25p, 1080/24p, 1080/23.98p, 720/59.94p, 720/50p</p> <p>NDI HX: 1920/1080p, 1280/720p *5</p> <p>Output</p> <p>Maximum 2 lines</p> <p>Possible output formats</p> <ul style="list-style-type: none"> • When system format is 4K <p>NDI® High Bandwidth: 2160/59.94p, 2160/50p, 2160/29.97p, 2160/25p, 2160/24p, 2160/23.98p</p> <ul style="list-style-type: none"> • When system format is 2K *1 *4 <p>NDI® High Bandwidth: 1080/59.94p, 1080/50p, 1080/29.97p, 1080/25p, 1080/24p, 1080/23.98p, 720/59.94p, 720/50p</p> <ul style="list-style-type: none"> • PGM, PVW, CLN, ME PGM, AUX1 to 4, MV1 and 2, and Key <p>Out can be allocated to the output.</p>
Footnote Description	<p>Support for NDI®HX is input only. Only NDI® High Bandwidth is supported for output.</p> <p>When the system format is 2K, mixed input of NDI® High Bandwidth and NDI® HX is possible.</p> <p>P/I conversion is possible for input when the system format is 2K.</p> <p>Not available when the system format is Psf.</p> <p>The frame rate for NDI® HX depends on the system format.</p>

