



Lanzamiento previsto para el primer trimestre de 2026

AW-RP200GJ

El controlador remoto de cámara de próxima generación revoluciona los flujos de trabajo de los operadores. El AW-RP200GJ, basado en la operatividad altamente reconocida de su predecesor (AW-RP150GJ), presenta nuevas y poderosas características, como una conveniente funcionalidad macro para ejecutar operaciones complejas de la cámara con facilidad y joysticks duales izquierdo y derecho para un control flexible. Estas innovaciones mejoran el rendimiento del controlador para producciones multicámara, incluso en entornos de grabación a gran escala, para elevar el valor del contenido de video.

Key Features

20 interruptores de selección múltiple para selección de cámara, recuperación de preajustes y ejecución macro

El primer controlador remoto de cámara de Panasonic compatible con la funcionalidad macro

Práctico segundo joystick a la izquierda (además del joystick principal a la derecha para el control de giro, inclinación y zoom o enfoque)

AW-RP200GJ

<https://latam.connect.panasonic.com/pe/es/productos/broadcast-y-proav/aw-rp200gj>

General -> Power Requirements	DC 12 V
General -> PoE	PoE++ IEEE802.3bt standard : DC 42 V to 57 V
General -> Weight	Approx. 3.5 kg (7.72 lb)
General -> Dimensions	364 mm x 178 mm x 245 mm (14-11/32 inches x 7 inches x 9-21/32 inches) (excluding protrusions)
Input Connector -> DC IN	DC 12 V IN, XLR 4-pin
Input/Output Connector -> LAN (IP CONT)	LAN (RJ-45)
Input/Output Connector -> TALLY / GPIO 1	GPIO x2 (DSUB 25-pin)
Input/Output -> LCD Display	7-inch Touch Panel GUI Monitor (WVGA(800×480))
Connection Specifications -> No. of Connectable Cameras	200 (IP), 3 (RS-422)
Connection Specifications -> No. of Camera Selection Buttons	20
Memory -> Preset Memory	No. of memory presets 100 per camera
Memory -> Tracing Memory	Maximum of 10 settings per camera (CAM1 ~ 10)
Input Connector -> 3G SDI IN	SMPTE424M/SMPTE292M/75Ω (BNC×1)
Output Connector -> 3G SDI OUT	SMPTE424M/SMPTE292M/75Ω (BNC×1)
Input/Output Connector -> LAN (SERIAL CONT 1-3)	RS-422 x3 (RJ-45)
Input/Output Connector -> USB Port	USB Type-A/Type-C (USB2.0)
Memory -> Macro Memory	No. of macros 100